CT12-V/3000 1/3



PRODUCT-DETAILS

CT12-V/3000 CT12-V/3000 Current transformer



General Information	
Extended Product Type	CT12-V/3000
Product ID	2CSG831250R1101
EAN	8012542610304
Catalog Description	CT12-V/3000 Current transformer
Long Description	CT12-V/3000 is used to transform primary currents to/5A secondary currents for c.a. measurement instruments

Technical	
Cable Use	Cable and Vertical bar
Current Rating	3000 A
Rated Primary Current (I pn)	3000 A
Rated Secondary Current (I_{sn})	5 A
Current Limit Function	FS 5
Frequency (f)	50 60 Hz
Apparent Power Output	3 V·A
Power Loss	24 W
Secondary Output	Plug-in connection

CT12-V/3000 2/3

Connection	
Accuracy	±0,5%
Model Number	Through-feed current converter
Number of Inputs	Primary 1
Mounting Type	Through Primary
Cable Cross-Section	3 x 35 mm
Rated Cross-Section	4 x 125 x 5 mm
Material Compliance	
	000044500449004
RoHS Information	2CSC445004K0201
RoHS Status RoHS Date	Following EU Directive 2002/95/EC August 18, 2005 and amendment 31/03/2006 0.00.00
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363
Environmental	
Ambient Air Temperature	Operation -5 50 °C
Degree of Protection	IP30
Environmental Information	See RoHS Information
Dimensions	
Product Net Width	109 mm
Product Net Height	26.5 mm
Product Net Depth / Length	41 mm
Product Net Weight	0.976 kg
Bore Diameter	18 mm
Ordering	
Package Level 1 Units Package Level 1 Gross	box 1 piece 1.03 kg
Weight Weight	1.00 kg
Certificates and Declarations	
Declaration of Conformity - CE	9AKK106713A5700
Installation	
Instructions and Manuals	No document needed
Popular Downloads	
Popular Downloads	9AKK107046A0430
Data Sheet, Technical Information	9AKK 107046A0430
Classifications	
<u> </u>	

CT12-V/3000 3/3

ETIM 8	EC002048 - Current transformer
ETIM 9	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85043121
eClass	V11.0 : 27210902
Object Classification Code	Т

Categories

 $Low\ Voltage\ Products\ and\ Systems\ \to\ Modular\ DIN\ Rail\ Products\ \to\ Energy\ Efficiency\ Devices\ \to\ Current\ Transformers$

