CT30/400 1/3



PRODUCT-DETAILS

CT30/400

CT30/400 Split core current transformer



General Information	
Extended Product Type	CT30/400
Product ID	2CSG101150R1101
EAN	8012542888109
Catalog Description	CT30/400 Split core current transformer
Long Description	CT30/400 is a split core current transformer used to transform primary currents to/5A secondary currents for c.a. measurement instruments

Technical	
Rated Primary Current (I pn)	400 A
Current Limit Function	FS 5
Frequency (f)	50 60 Hz
Secondary Output Connection	Screw connection
Accuracy	±0,5%
Model Number	Through-feed current converter
Number of Inputs	Primary 1
Mounting Type	Through Primary
Rated Cross-Section	2 x 30 x 10 mm

CT30/400 2/3

Material Compliance		
RoHS Information	2CSC445004K0901	
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment	
RoHS Date	03/04/2006 0.00.00	
Conflict Minerals	9AKK108468A3363	
Reporting Template (CMRT)		
Environmental		
Ambient Air Temperature	Operation -25 50 °C	
Degree of Protection Environmental Information	IP20 See RoHS Information	
Dimensions		
Product Net Width	0.093 m	
Product Net Height Product Net Denth /	0.106 m 0.034 m	
Product Net Depth / Length	0.034 m	
Product Net Weight	0.850 kg	
Bore Diameter	156 mm	
Ordering		
Package Level 1 Units	box 1 piece	
Package Level 1 Gross	0.85 kg	
Weight E-Number (Finland)	6719015	
Number (Filianu)	0713013	
Certificates and Declarations		
Declaration of Conformity CE	9AKK106713A5700	
Installation		
Instructions and Manuals	2CSC446012B0201	
Popular Downloads		
Data Sheet, Technical	9AKK107046A0430	
nformation		
Classifications		
ETIM 8	EC002048 - Current transformer	
ETIM 9	EC002046 - Current transformer	
	5. Small Equipment (No External Dimension More Than 50 cm)	
WEEE Category		
WEEE Category WEEE B2C / B2B	Business To Consumer	
	85043121	
WEEE B2C / B2B		

CT30/400 3/3

Object Classification Code

Categories

 $Low\ Voltage\ Products\ \rightarrow\ Modular\ DIN\ Rail\ Products\ \rightarrow\ Energy\ Efficiency\ Devices\ \rightarrow\ Current\ Transformers$

