



PRODUCT-DETAILS

CT80/250**CT80/250 Split core current transformer****General Information**

Extended Product Type	CT80/250
Product ID	2CSG201130R1101
EAN	8012542888208
Catalog Description	CT80/250 Split core current transformer
Long Description	CT80/250 is a split core current transformer used to transform primary currents to.../5A secondary currents for c.a. measurement instruments

Technical

Rated Primary Current (I_{pn})	250 A
Rated Secondary Current (I_{sn})	4 A
Current Limit Function	FS 5
Frequency (f)	50 ... 60 Hz
Apparent Power Output	1000 V·A
Power Loss	2 V·A
Secondary Output Connection	Screw connection

Accuracy	±0,5%
Model Number	Through-feed current converter
Number of Inputs	Primary 1
Mounting Type	Through Primary
Rated Cross-Section	3 x 80 x 10 mm

Material Compliance

RoHS Information	2CSC445004K0901
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment
RoHS Date	03/04/2006 0.00.00
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Environmental

Ambient Air Temperature	Operation -25 ... 50 °C
Degree of Protection	IP20
Environmental Information	See RoHS Information

Dimensions

Product Net Width	0.125 m
Product Net Height	0.152 m
Product Net Depth / Length	0.034 m
Product Net Weight	1.100 kg

Ordering

Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	1.1 kg

Certificates and Declarations

Declaration of Conformity - CE	9AKK106713A5700
--------------------------------	-----------------

Installation

Instructions and Manuals	2CSC446012B0201
--------------------------	-----------------

Popular Downloads

Data Sheet, Technical Information	9AKK107046A0430
-----------------------------------	-----------------

Classifications

ETIM 8	EC002048 - Current transformer
ETIM 9	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85043121
eClass	V11.0 : 27210902
Object Classification Code	T

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Current Transformers

