TRFM/600 1/3



PRODUCT-DETAILS

TRFM/600 Current modular transformer



General Information	
Extended Product Type	TRFM/600
Product ID	2CSM100160R1111
EAN	8012542047506
Catalog Description	TRFM/600 Current modular transformer
Long Description	Used to transform primary currents into/5 A low secondary currents indirectly supplying power to analogue and digital measurement instrument devices. They have through primary and modular case and DIN rail fasten system.

Technical	
Current Rating	600 A
Rated Primary Current (I	600 A
Rated Secondary Current (I_{sn})	5 A
Current Limit Function	FS 5
Apparent Power Output	8 V·A
Secondary Output Connection	Screw connection
Model Number	Through-feed current converter

TRFM/600 2/3

Number of Inputs	Primary 1
Mounting Type	DIN-Rai
Material Compliance	
RoHS Information	9AKK106713A5716
RoHS Status	Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019
RoHS Date	20230928
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363
Environmental	
Degree of Protection	IP20
Environmental Information	See RoHS Information
Dimensions	
Product Net Width	0.065 m
Product Net Height	0.075 m
Product Net Depth / Length	0.100 m
Product Net Weight	0.195 kg
Bore Diameter	155 mm
Ordering	
Package Level 1 Units	box 1 piece
Package Level 1 Gross	0.859 kg
Weight E-Number (Finland)	6701051
E-Nambel (Finialia)	0701001
Certificates and Declarations	
Declaration of Conformity - CE	9AKK106713A5716
Installation	
Instructions and Manuals	No document needed
Popular Downloads	
Data Sheet, Technical Information	9AKK107046A0430
Classifications	
ETIM 8	EC002048 - Current transformer
ETIM 9 WEEE Category	EC002048 - Current transformer 5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
© 2024 ABB. All rights reserved.	2024/04/12 Subject to chan

TRFM/600 3/3

 CN8
 85043121

 eClass
 V11.0 : 27210902

 Object Classification Code
 T

Categories

 $Low\ Voltage\ Products\ and\ Systems \rightarrow Modular\ DIN\ Rail\ Products \rightarrow Energy\ Efficiency\ Devices \rightarrow Current\ Transformers$

