



 PRODUCT-DETAILS

CT6/250

CT6/250 Current transformer



General Information

Extended Product Type	CT6/250
Product ID	2CSG421130R1101
EAN	8012542605508
Catalog Description	CT6/250 Current transformer
Long Description	CT6/250 is used to transform primary currents to $\dots/5A$ secondary currents for c.a. measurement instruments

Technical

Cable Use	Cable and Horizontal bar
Rated Primary Current (I_{pn})	250 A
Rated Secondary Current (I_{sn})	5 A
Current Limit Function	FS 5
Frequency (f)	50 ... 60 Hz
Power Loss	16 W
Secondary Output Connection	Screw connection

Accuracy	±0,5%
Model Number	Wound primary current converter
Number of Inputs	Primary 1
Mounting Type	Through Primary
Cable Cross-Section	50 mm
Rated Cross-Section	60 x 20 mm

Material Compliance

RoHS Information	2CSC445004K0201
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment
RoHS Date	31/03/2006 0.00.00
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Environmental

Ambient Air Temperature	Operation -5 ... 50 °C
Degree of Protection	IP30
Environmental Information	See RoHS Information

Dimensions

Product Net Width	105 mm
Product Net Height	26.5 mm
Product Net Depth / Length	61 mm
Product Net Weight	0.450 kg
Bore Diameter	0 mm

Ordering

Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	1 kg

Certificates and Declarations

Declaration of Conformity - CE	9AKK106713A5700
--------------------------------	-----------------

Installation

Instructions and Manuals	2CSC446012B0201
--------------------------	-----------------

Popular Downloads

Data Sheet, Technical	9AKK107046A0430
-----------------------	-----------------

Information

Classifications

ETIM 8	EC002048 - Current transformer
ETIM 9	EC002048 - Current transformer
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)
WEEE B2C / B2B	Business To Consumer
CN8	85043121
eClass	V11.0 : 27210902
Object Classification Code	T

Categories

Low Voltage Products and Systems → Modular DIN Rail Products → Energy Efficiency Devices → Current Transformers



360°